Proper Orthogonal Decomposition: Theory and Reduced-Order Modeling

Stefan Volkwein

M. Gubisch, O. Lass (U. Konstanz) M. Hinze (U Hamburg), K. Kunisch (U Graz)

University of Konstanz, Department of Mathematics and Statistics, Numerics & Optimization Group

Summerschool on Redued-Basis Methods, München, 16. September 2013





< 日 > < 同 > < 回 > < 回 > :

Motivation for our Research Areas (Grimm, Gubisch, Iapichino, Lass, Mancini, Trenz, V., Wesche)

- Problem: time-variant, nonlinear, parametrized PDE systems
- Efficient and reliable numerical simulation in multi-query cases → finite element or finite volume discretizations too complex
- Multi-query examples
 - fast simulation for different parameters on small computers
 - parameter estimation, optimal design and feedback control
 - \rightarrow usage of a reduced-order SURROGATE MODEL
- Time-variant, nonlinear coupled PDEs \rightarrow methods from linear system theory not directly applicable
- Nonlinear model-order reduction
 - \rightarrow proper orthogonal decomposition and reduced-basis method
- Error control for reduced-order model
 - \rightarrow new a-priori and a-posteriori error analysis

PDE — Partial Differential Equation

Singular Value Decomposition (SVD)

- Given vectors: $y_1, \ldots, y_n \in \mathbb{R}^m$
- Data matrix: $Y = [y_1, \dots, y_n] \in \mathbb{R}^{m \times n}$
- Singular value decomposition: $U \in \mathbb{R}^{m \times m}$, $V \in \mathbb{R}^{n \times n}$ orthogonal

$$U^{\top}YV = \begin{pmatrix} D & 0 \\ 0 & 0 \end{pmatrix} = \Sigma \in \mathbb{R}^{m \times n}$$

with $D = \operatorname{diag}(\sigma_1, \ldots, \sigma_d) \in \mathbb{R}^{d \times d}$

- Singular values: $\sigma_1 \ge \ldots \ge \sigma_d > 0$, rank Y = d
- Frobenius norm:

$$\|Y\|_{F} = \left(\sum_{i=1}^{m} \sum_{j=1}^{n} Y_{ij}^{2}\right)^{1/2} \text{ for } Y \in \mathbb{R}^{m \times n}$$

Approximation quality:

$$\|\mathbf{Y}-\mathbf{Y}^{\ell}\|_{F}^{2} = \sum_{i=\ell+1}^{d} \sigma_{i}^{2}$$

with
$$Y^{\ell} = U \begin{pmatrix} D^{\ell} & 0 \\ 0 & 0 \end{pmatrix} V^{\top}$$
 and $D^{\ell} = \text{diag}(\sigma_1, \dots, \sigma_{\ell})$

Approximation
$$||Y - Y^{\ell}||_F^2 = \sum_{i=\ell+1}^{d} \sigma_i^2$$
 for a given Photo

0,5% der Matrixbasis -> 45% Information



10% der Matrixbasis -> 85% Information



1% der Matrixbasis -> 56% Information



20% der Matrixbasis -> 92% Information



5% der Matrixbasis -> 76% Information



Originalbild



<ロ> <部> <部> <き> <き><

э

- The method of Proper Orthogonal Decomposition (POD)
- Reduced-order modeling utilizing the POD method

æ

The Method of Proper Orthogonal Decomposition (POD)

Topics:

- Definition of a (discrete variant of the) POD basis
- Efficient computation of a POD basis
- POD for dynamical systems
- A continuous variant of the POD basis and asymptotic analysis

POD as a Minimization Problem

- Given multiple snapshots: $\{y_i^k\}_{i=1}^n \subset X$, $1 \le k \le \rho$, with a (real) Hilbert space X
- Snapshot subspace:

$$\mathcal{V} = \operatorname{span}\left\{y_j^k \mid 1 \le j \le n \text{ and } 1 \le k \le \mathscr{O}\right\} \subset X$$

with dimension $d \in \{1, \dots, \min(n_{\mathcal{P}}, \dim X)\}$

• Proper Orthogonal Decomposition (POD): for any $\ell \in \{1, ..., d\}$ solve

$$\min \sum_{k=1}^{\ell^{p}} \sum_{j=1}^{n} \alpha_{j} \left\| \boldsymbol{y}_{j}^{k} - \sum_{i=1}^{\ell} \left\langle \boldsymbol{y}_{j}^{k}, \boldsymbol{\psi}_{i} \right\rangle_{X} \boldsymbol{\psi}_{i} \right\|_{X}^{2} \quad \text{s.t.} \quad \{\boldsymbol{\psi}_{i}\}_{i=1}^{\ell} \subset X \text{ and } \langle \boldsymbol{\psi}_{i}, \boldsymbol{\psi}_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \quad (\mathbf{P}^{\ell})$$

with positive weights α_i

- Optimal solution to (P^{ℓ}): POD basis $\{\bar{\psi}_i\}_{i=1}^{\ell}$ of rank ℓ
- Orthogonal projection: define $\mathscr{P}^{\ell}: X \to \mathcal{V}^{\ell} = \operatorname{span} \{ \bar{\psi}_1, \dots, \bar{\psi}_{\ell} \} \subset \mathcal{V}$ by

$$\mathscr{P}^{\ell}\psi = \sum_{i=1}^{\ell} \langle \psi, \bar{\psi}_i \rangle_X \bar{\psi}_i \quad \text{for } \psi \in X$$

$$\Rightarrow \sum_{k=1}^{\wp} \sum_{j=1}^{n} \alpha_j \left\| y_j^k - \sum_{i=1}^{\ell} \left\langle y_j^k, \psi_i \right\rangle_X \psi_i \right\|_X^2 = \sum_{k=1}^{\wp} \sum_{j=1}^{n} \alpha_j \left\| y_j^k - \mathscr{P}^\ell y_j^k \right\|_X^2$$

Stefan Volkwein

Equivalent POD Formulation

• POD as a minimization problem: for any $\ell \in \{1, ..., d\}$ solve

 $\min \sum_{k=1}^{\ell^2} \sum_{j=1}^n \alpha_j \left\| \boldsymbol{y}_j^k - \sum_{i=1}^{\ell} \left\langle \boldsymbol{y}_j^k, \boldsymbol{\psi}_i \right\rangle_X \boldsymbol{\psi}_i \right\|_X^2 \quad \text{s.t.} \quad \{\boldsymbol{\psi}_i\}_{i=1}^{\ell} \subset X \text{ and } \left\langle \boldsymbol{\psi}_i, \boldsymbol{\psi}_j \right\rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \quad (\mathbf{P}^\ell)$

• Orthonormal basis elements: for $1 \le j \le n$ and $1 \le k \le p$ we have

$$\left\|\boldsymbol{y}_{j}^{k}-\sum_{i=1}^{\ell}\left\langle\boldsymbol{y}_{j}^{k},\boldsymbol{\psi}_{i}\right\rangle_{X}\boldsymbol{\psi}_{i}\right\|_{X}^{2}=\left\|\boldsymbol{y}_{j}^{k}\right\|_{X}^{2}-\sum_{i=1}^{\ell}\left\langle\boldsymbol{y}_{j}^{k},\boldsymbol{\psi}_{i}\right\rangle_{X}^{2}$$

• POD as a maximization problem: for $\ell \in \{1, ..., d\}$ solve

$$\max \sum_{k=1}^{\ell^{p}} \sum_{j=1}^{n} \alpha_{j} \sum_{i=1}^{\ell} \langle y_{j}^{k}, \psi_{i} \rangle_{X}^{2} \quad \text{s.t.} \quad \{\psi_{i}\}_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{i} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \end{cases}$$

 \Rightarrow maximize the first ℓ Fourier coefficient $\left(\sum_{j=1}^{\ell} \langle y_j^k, \psi_j \rangle_X^2\right)$ on average $\left(\sum_{j=1}^{n} \alpha_j\right)$ for all k

• Lagrange functional for $(\hat{\mathbf{P}}^{\ell})$: for $\Psi = (\psi_1, \dots, \psi_\ell) \in X^{\ell}$ and $\Lambda = ((\lambda_{ij})) \in \mathbb{R}^{\ell \times \ell}$ define

$$\mathscr{L}(\Psi, \Lambda) = \sum_{k=1}^{\wp} \sum_{j=1}^{n} \alpha_j \sum_{i=1}^{\ell} \langle y_j^k, \psi_i \rangle_{\chi}^2 + \sum_{i=1}^{\ell} \sum_{j=1}^{\ell} \lambda_{ij} (\delta_{ij} - \langle \psi_i, \psi_j \rangle_{\chi})$$

Lagrangian Framework in (Infinite Dimensional) Optimization

• POD as a maximization problem: for any $\ell \in \{1, ..., d\}$ solve

$$\max \sum_{k=1}^{\ell^2} \sum_{j=1}^n \alpha_j \sum_{i=1}^{\ell} \langle y_j^k, \psi_i \rangle_X^2 \quad \text{s.t.} \quad \{\psi_i\}_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le j \le \ell \qquad (\hat{\mathbf{P}}^{\ell})_{i=1}^{\ell} \subset X \text{ and }$$

• Lagrange functional for (\hat{P}^{ℓ}) : for $\Psi = (\psi_1, ..., \psi_{\ell}) \in X^{\ell}$ and $\Lambda = ((\lambda_{ij})) \in \mathbb{R}^{\ell \times \ell}$ define

$$\mathscr{L}(\Psi, \Lambda) = \sum_{k=1}^{\ell} \sum_{j=1}^{n} \alpha_j \sum_{i=1}^{\ell} \langle y_j^k, \psi_i \rangle_X^2 + \sum_{i=1}^{\ell} \sum_{j=1}^{\ell} \lambda_{ij} (\delta_{ij} - \langle \psi_i, \psi_j \rangle_X)$$

- Necessary optimality conditions: let $\bar{\Psi} = (\bar{\psi}_1, ..., \bar{\psi}_\ell)$ denote a solution to $(\hat{\mathbf{P}}^\ell)$
- Constraint qualification condition: there is a Lagrange multiplier $\bar{\Lambda} = ((\bar{\lambda}_{ij}))$ with

$$\frac{\partial \mathscr{L}}{\partial \psi_i}(\bar{\Psi},\bar{\Lambda}) = 0 \text{ in } X \text{ for } 1 \le i \le \ell \quad \text{and} \quad \frac{\partial \mathscr{L}}{\partial \lambda_{ij}}(\bar{\Psi},\bar{\Lambda}) = 0 \text{ in } \mathbb{R} \text{ for } 1 \le i,j \le \ell$$

 \Rightarrow first-order necessary optimality conditions for $(\hat{\mathbf{P}}^{\ell})$

First-Order Necessary Optimality Conditions

• POD as a maximization problem: for any $\ell \in \{1, ..., d\}$ solve

$$\max\sum_{k=1}^{N}\sum_{j=1}^{n}\alpha_{j}\sum_{i=1}^{\ell}\langle y_{j}^{k},\psi_{i}\rangle_{\chi}^{2} \quad \text{s.t.} \quad \{\psi_{i}\}_{i=1}^{\ell}\subset X \text{ and } \langle \psi_{i},\psi_{j}\rangle_{\chi}=\delta_{ij}, \ 1\leq i,j\leq\ell \qquad (\hat{\mathbf{P}}^{\ell})$$

• First-order necessary optimality conditions: $\bar{\Psi} = (\bar{\psi}_1, \dots, \bar{\psi}_\ell)$ and $\bar{\Lambda} = ((\bar{\lambda}_{ij}))$ satisfy

$$\frac{\partial \mathscr{L}}{\partial \psi_i}(\bar{\Psi},\bar{\Lambda}) = 0 \text{ in } X \text{ for } 1 \le i \le \ell \quad \text{and} \quad \langle \psi_i,\psi_j \rangle_{\chi} = \delta_{ij} \text{ for } 1 \le i,j \le \ell$$

- Summation operator: define $\mathscr{R}: X \to X$ as $\mathscr{R}\psi = \sum_{k=1}^{p} \sum_{j=1}^{n} \alpha_j \langle \psi, y_j^k \rangle_X y_j^k$ for $\psi \in X$
- Theorem: X separable Hilbert space
 - a) \mathscr{R} is linear, compact, selfadjoint and nonnegative
 - b) there are eigenfunctions $\{\bar{\psi}_i\}_{i\in\mathbb{J}}$ and eigenvalues $\{\bar{\lambda}_i\}_{i\in\mathbb{J}}$ with

$$\mathscr{R}\bar{\psi}_{i} = \bar{\lambda}_{i}\bar{\psi}_{i}, \quad \bar{\lambda}_{1} \geq \bar{\lambda}_{2} \geq \ldots \geq \bar{\lambda}_{d} > \bar{\lambda}_{d+1} = \ldots = 0$$

c)
$$\{\bar{\psi}_i\}_{i=1}^{\ell}$$
 solves $(\hat{\mathbf{P}}^{\ell})$ and (\mathbf{P}^{ℓ})
d) $\sum_{k=1}^{\rho} \sum_{j=1}^{n} \alpha_j \sum_{i=1}^{\ell} \langle y_j^k, \bar{\psi}_i \rangle_X^2 = \sum_{i=1}^{\ell} \bar{\lambda}_i, \quad \sum_{k=1}^{\rho} \sum_{j=1}^{n} \alpha_j \left\| y_j^k - \sum_{i=1}^{\ell} \langle y_j^k, \bar{\psi}_i \rangle_X \bar{\psi}_i \right\|_X^2 = \sum_{i>\ell} \bar{\lambda}_i$

POD Basis Computation

• POD: for any $\ell \in \{1, \ldots, d\}$ solve

 $\min\sum_{k=1}^{p} \sum_{j=1}^{n} \alpha_{j} \left\| \boldsymbol{y}_{j}^{k} - \sum_{i=1}^{\ell} \left\langle \boldsymbol{y}_{j}^{k}, \boldsymbol{\psi}_{i} \right\rangle_{X} \boldsymbol{\psi}_{i} \right\|_{X}^{2} \quad \text{s.t.} \quad \{\boldsymbol{\psi}_{i}\}_{i=1}^{\ell} \subset X \text{ and } \langle \boldsymbol{\psi}_{i}, \boldsymbol{\psi}_{j} \rangle_{X} = \delta_{ij}, \ 1 \leq i, j \leq \ell \quad (\mathbf{P}^{\ell})$

• Eigenvalue problem:

$$\mathscr{R}\bar{\psi}_{i} = \sum_{k=1}^{\rho} \sum_{j=1}^{n} \alpha_{j} \langle \bar{\psi}_{i}, y_{j}^{k} \rangle_{X} y_{j}^{k} = \bar{\lambda}_{i} \bar{\psi}_{i} \text{ for } 1 \le i \le \ell, \quad \bar{\lambda}_{1} \ge \bar{\lambda}_{2} \ge \ldots \ge \bar{\lambda}_{\ell} > 0$$

• Approximation quality: POD basis $\{\bar{\psi}_i\}_{i=1}^{\ell}$ of rank ℓ

$$\sum_{k=1}^{\ell^2} \sum_{j=1}^n \alpha_j \left\| \boldsymbol{y}_j^k - \sum_{i=1}^{\ell} \langle \boldsymbol{y}_j^k, \bar{\boldsymbol{\psi}}_i \rangle_{\boldsymbol{X}} \, \bar{\boldsymbol{\psi}}_i \right\|_{\boldsymbol{X}}^2 = \sum_{i>\ell} \bar{\lambda}_i$$

 \Rightarrow for fastly decreasing $\bar{\lambda}_i$'s good approximation quality even for small $\ell \ll d = \dim V$

In practical computations: heuristical choice for l by posing

$$\mathscr{E}(\ell) = \frac{\sum_{i=1}^{\ell} \bar{\lambda}_i}{\sum_{i \in \mathcal{I}} \bar{\lambda}_i} = \frac{\sum_{i=1}^{\ell} \bar{\lambda}_i}{\sum_{k=1}^{\ell} \sum_{j=1}^{n} \alpha_j \|y_j^k\|_{\chi}^2} \approx 99\%$$

 $i \Rightarrow \{\overline{\lambda}_i\}_{i>\ell}$ not required for the computation of $\mathscr{E}(\ell)$

Example 1: POD in the Euclidean Space $X = \mathbb{R}^m$

- Setting: $X = \mathbb{R}^m$, $\{y_j\}_{j=1}^n \subset \mathbb{R}^m$ ($\wp = 1$), $Y := [y_1| \dots |y_n] \in \mathbb{R}^{m \times n}$, $\alpha_j = 1$ for $1 \le j \le n$
- POD: for any $\ell \in \{1, \ldots, d\}$ solve

$$\min\sum_{j=1}^{n} \left\| \boldsymbol{y}_{j} - \sum_{i=1}^{\ell} \left(\boldsymbol{y}_{j}^{\top} \boldsymbol{\psi}_{i} \right) \boldsymbol{\psi}_{i} \right\|_{\mathbb{R}^{m}}^{2} \quad \text{s.t.} \quad \{\boldsymbol{\psi}_{i}\}_{i=1}^{\ell} \subset \mathbb{R}^{m} \text{ and } \boldsymbol{\psi}_{i}^{\top} \boldsymbol{\psi}_{j} = \boldsymbol{\delta}_{ij}, \ 1 \leq i, j \leq \ell$$

- Summation operator: $\mathscr{R}\psi = \sum_{j=1}^{n} (\psi^{\top} y_j) y_j = YY^{\top} \psi$ for $\psi \in \mathbb{R}^m$
- Symmetric eigenvalue problem:

$$YY^{\top} \, \bar{\psi}_i = \bar{\lambda}_i \bar{\psi}_i \text{ for } 1 \leq i \leq \ell, \quad \bar{\lambda}_1 \geq \bar{\lambda}_2 \geq \ldots \geq \bar{\lambda}_\ell > 0$$

• Singular value decomposition (SVD): $\bar{\sigma}_1 \ge \ldots \ge \bar{\sigma}_d > 0$

$$\Psi^{\top} Y \Phi = \begin{pmatrix} \Sigma_{d} & 0 \\ 0 & 0 \end{pmatrix} =: \Sigma \in \mathbb{R}^{m \times n}$$

with $\Psi = [\bar{\psi}_1 | \dots | \bar{\psi}_m] \in \mathbb{R}^{m \times m}$, $\Phi = [\bar{\phi}_1 | \dots | \bar{\phi}_n] \in \mathbb{R}^{n \times n}$ orthogonal, $\Sigma_d = \text{diag}(\bar{\sigma}_1, \dots, \bar{\sigma}_d)$

• Relation between POD and SVD: for $1 \le i \le \ell$ we have

$$\underbrace{\begin{array}{l} Y\bar{\phi}_{i}=\bar{\sigma}_{i}\bar{\psi}_{i}, \quad Y^{\top}\bar{\psi}_{i}=\bar{\sigma}_{i}\bar{\phi}_{i}, \\ \text{SVD (stability)} \end{array}}_{\text{SVD (stability)}} \quad \bar{\sigma}_{i}^{2}=\bar{\lambda}_{i}, \quad \underbrace{\begin{array}{l} YY^{\top}\bar{\psi}_{i}=\bar{\lambda}_{i}\bar{\psi}_{i}, \\ \text{if } m < n \end{array}}_{\text{if } m < n} \quad \underbrace{\begin{array}{l} Y^{\top}Y\bar{\phi}_{i}=\bar{\lambda}_{i}\bar{\phi}_{i} \\ \text{if } n < m \end{array}}_{\text{if } n < m}$$

Example 2: POD in the Euclidean Space $X = \mathbb{R}^m$ with Weighted Inner Product

- Setting: $X = \mathbb{R}^m$, $\{y_j\}_{j=1}^n \subset \mathbb{R}^m$ ($\wp = 1$), $Y := [y_1|...|y_n] \in \mathbb{R}^{m \times n}$
- Inner product: $\langle \psi, \tilde{\psi} \rangle_X = \langle \psi, \tilde{\psi} \rangle_W = \psi^\top W \tilde{\psi}$ for $\psi, \tilde{\psi} \in \mathbb{R}^m$ and $W = W^\top \succ 0$
- POD: for any $\ell \in \{1, \ldots, d\}$ solve

$$\min \sum_{j=1}^{n} \alpha_{j} \left\| y_{j} - \sum_{i=1}^{\ell} \left\langle y_{j}, \psi_{i} \right\rangle_{W} \psi_{i} \right\|_{W}^{2} \quad \text{s.t.} \quad \left\{ \psi_{i} \right\}_{i=1}^{\ell} \subset \mathbb{R}^{m} \text{ and } \left\langle \psi_{i}, \psi_{j} \right\rangle_{W} = \delta_{ij}, \ 1 \leq i, j \leq \ell$$

- Summation operator: $\mathscr{R} = YDY^{\top}W$ and $D = \operatorname{diag}(\alpha_1, \dots, \alpha_n) \in \mathbb{R}^{n \times n}$
- Symmetric eigenvalue problem: $\hat{Y} = W^{1/2} Y D^{1/2}$ and $\hat{Y} \hat{Y}^{\top} = W^{1/2} Y D Y^{\top} W^{1/2}$

$$\hat{Y}\hat{Y}^{ op}\psi_{i}=ar{\lambda}_{i}\psi_{i} ext{ for } 1\leq i\leq \ell, \quad ar{\lambda}_{1}\geq ar{\lambda}_{2}\geq \ldots\geq ar{\lambda}_{\ell}>0$$

and set $\bar{\psi}_i = W^{-1/2} \psi_i$ for $1 \le i \le \ell$

• Singular value decomposition: $\hat{Y}^{\top}\hat{Y} = D^{1/2}Y^{\top}WYD^{1/2}$ and $\bar{\sigma}_i^2 = \bar{\lambda}_i$

$$\hat{Y}^{\top} \, \hat{Y} \phi_i = \bar{\lambda}_i \phi_i \text{ for } 1 \leq i \leq \ell, \quad \bar{\lambda}_1 \geq \bar{\lambda}_2 \geq \ldots \geq \bar{\lambda}_\ell > 0$$

and set $\bar{\psi}_i = YD^{1/2}\phi_i/\bar{\sigma}_i$ for $1 \le i \le \ell \Rightarrow$ no computation of $W^{1/2}$

• Multiple snapshots: set $Y_k = [y_1^k| \dots |y_n^k] \in \mathbb{R}^{m \times n}$ and

 $\mathscr{R} = \left(Y_1 D Y_1^\top + \ldots + Y_{\wp} D Y_{\wp}^\top\right) W \in \mathbb{R}^{m \times m}$

Application to Nonlinear Dynamical Systems

• Dynamical system in Hilbert space X:

 $\dot{y}(t) = f(t, y(t); \mu)$ for $t \in (t_\circ, t_f]$, $y(t_\circ) = y_\circ \in X$

with given parameter $\mu \in \mathfrak{D}_{ad}$, initial value y_\circ and (smooth) nonlinearity f

- State trajectory: there is a unique solution $y(t; \mu) \in X$ for fixed parameter $\mu \in \mathcal{D}_{ad}$
- Multiple snapshots: for grids $t_o = t_1 < ... < t_n \le t_f$ and $\{\mu^k\}_{k=1}^{\wp} \subset \mathcal{D}$ let $y_i^k \approx \gamma(t_i; \mu^k)$
- Discrete variant of POD: for any $\ell \in \{1, \ldots, d\}$ solve

$$\min \sum_{k=1}^{\ell^2} \sum_{j=1}^n \alpha_j \left\| y_j^k - \sum_{i=1}^{\ell} \langle y_j^k, \psi_i \rangle_{\chi} \psi_i \right\|_{\chi}^2 \quad \text{s.t.} \quad \{\psi_i\}_{i=1}^{\ell} \subset X \text{ and } \langle \psi_i, \psi_j \rangle_{\chi} = \delta_{ij}, \ 1 \le i, j \le \ell \quad (\mathbf{P}^{\ell})$$

with positive weights α_j (compare Greedy-POD strategy)

- Questions: a) How to choose "good" time instances t_j for the snapshots?
 b) What are appropriate positive weights {α_j}ⁿ_{i=1}?
- Continuous variant of POD: for $y^k(t) = y(t; \mu^k)$, $1 \le k \le \wp$, and any $\ell \in \{1, ..., d\}$ solve

$$\min\sum_{k=1}^{\ell^{2}}\int_{t_{o}}^{t_{f}}\left\|\boldsymbol{\gamma}^{k}(t)-\sum_{i=1}^{\ell}\langle\boldsymbol{\gamma}^{k}(t),\boldsymbol{\psi}_{i}\rangle_{X}\boldsymbol{\psi}_{i}\right\|_{X}^{2}\mathrm{d}t \text{ s.t. } \{\boldsymbol{\psi}_{i}\}_{i=1}^{\ell}\subset X, \ \langle\boldsymbol{\psi}_{i},\boldsymbol{\psi}_{j}\rangle_{X}=\boldsymbol{\delta}_{ij}, \ 1\leq i,j\leq\ell \quad (\mathbf{P}_{\infty}^{\ell})$$

Stefan Volkwein

▲□▶ ▲□▶ ▲三▶ ▲三▶ 三 のQ@

Continuous and Discrete Variant of the POD Method

• Dynamical system in Hilbert space X:

$$\dot{\mathbf{y}}(t) = f(t, \mathbf{y}(t); \mu)$$
 for $t \in (t_\circ, t_f], \quad \mathbf{y}(t_\circ) = \mathbf{y}_\circ \in X$

- Given multiple snapshots: solutions $y^k(t) = y(t; \mu^k) \in X$ for parameters $\{\mu^k\}_{k=1}^{p} \subset \mathcal{D}$
- Snapshot subspace:

$$\mathcal{V} = \operatorname{span}\left\{ \gamma^k(t) \, | \, t \in [t_0, T] \text{ and } 1 \le k \le \wp
ight\} \subset X \quad \text{with dimension } d^\infty \le \infty$$

• Continuous variant of POD: for any $\ell \in \{1, ..., d\}$ solve

$$\min\sum_{k=1}^{\ell^2} \int_{t_o}^{t_f} \left\| y^k(t) - \sum_{i=1}^{\ell} \langle y^k(t), \psi_i \rangle_X \psi_i \right\|_X^2 \mathrm{d}t \text{ s.t. } \{\psi_i\}_{i=1}^{\ell} \subset X, \ \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \quad (\mathbf{P}^{\ell}_{\infty})$$

- Integral operator: define $\mathscr{R}^{\infty}: X \to X$ as $\mathscr{R}^{\infty} \psi = \sum_{k=1}^{p} \int_{t_0}^{t_f} \langle \psi, y^k(t) \rangle_X y^k(t) dt$ for $\psi \in X$
- Discrete variant of POD: for $y_j^k \approx y^k(t_j)$ and any $\ell \in \{1, ..., d\}$ solve

$$\min \sum_{k=1}^{\ell^{2}} \sum_{j=1}^{n} \alpha_{j} \left\| y_{j}^{k} - \sum_{i=1}^{\ell} \left\langle y_{j}^{k}, \psi_{i} \right\rangle_{\chi} \psi_{i} \right\|_{\chi}^{2} \quad \text{s.t.} \quad \{\psi_{i}\}_{i=1}^{\ell} \subset X \text{ and } \langle \psi_{i}, \psi_{j} \rangle_{\chi} = \delta_{ij}, \ 1 \leq i, j \leq \ell \quad (\mathbf{P}^{\ell})$$

• Summation operator: $\mathscr{R}^n : X \to X$ with $\mathscr{R}^n \psi = \sum_{k=1}^p \sum_{j=1}^n \alpha_j \langle \psi, y_j^k \rangle_X y_j^k$ for $\psi \in X$

Stefan Volkwein

Asymptotic Analysis (Kunisch/V.'02)

• Continuous variant of POD: for any $\ell \in \{1, \dots, d\}$ solve

$$\min\sum_{k=1}^{\ell^{2}} \int_{t_{o}}^{t_{f}} \left\| y^{k}(t) - \sum_{i=1}^{\ell} \langle y^{k}(t), \psi_{i} \rangle_{X} \psi_{i} \right\|_{X}^{2} \mathrm{d}t \, \mathrm{s.t.} \, \left\{ \psi_{i} \right\}_{i=1}^{\ell} \subset X, \, \left\langle \psi_{i}, \psi_{j} \right\rangle_{X} = \delta_{ij}, \, 1 \leq i, j \leq \ell \quad (\mathbf{P}_{\omega}^{\ell})$$

• Operators:
$$\mathscr{R}^{\infty}\psi = \sum_{k=1}^{\rho} \int_{t_0}^{t_f} \langle \psi, y^k(t) \rangle_X y^k(t) dt$$
 and $\mathscr{R}^n \psi = \sum_{k=1}^{\rho} \sum_{j=1}^{n} \alpha_j \langle \psi, y_j^k \rangle_X y_j^k$

Theorem (Hilbert-Schmidt, Riesz-Schauder theorems; Perturbation theory (Kato'66))

X separable, $y^k \in H^1(t_o, t_f; X)$, choose α_j as trapezoidal weights

- a) \mathscr{R}^{∞} is linear, compact, selfadjoint and nonnegative
- b) there are eigenfunctions $\{\bar{\psi}_i^{\infty}\}_{i\in\mathbb{J}}$ and eigenvalues $\{\bar{\lambda}_i^{\infty}\}_{i\in\mathbb{J}}$ with

$$\mathscr{R}^{\infty}\bar{\psi}_{i}^{\infty}=\bar{\lambda}_{i}^{\infty}\bar{\psi}_{i}^{\infty},\quad\bar{\lambda}_{1}^{\infty}\geq\bar{\lambda}_{2}^{\infty}\geq\ldots\geq0,\quad\lim_{i\to\infty}\bar{\lambda}_{i}^{\infty}=0$$

c) $\{ar{\psi}_i^\infty\}_{i=1}^\ell$ solves (\mathbf{P}_∞^ℓ)

$$d) \sum_{k=1}^{\ell} \int_{t_o}^{t_f} \sum_{i=1}^{\ell} \langle y^k(t), \bar{\psi}_i^{\infty} \rangle_X^2 dt = \sum_{i=1}^{\ell} \bar{\lambda}_i^{\infty}, \sum_{k=1}^{\ell} \int_{t_o}^{t_f} \left\| y^k(t) - \sum_{i=1}^{\ell} \langle y^k(t), \bar{\psi}_i^{\infty} \rangle_X \bar{\psi}_i^{\infty} \right\|_X^2 dt = \sum_{i>\ell} \bar{\lambda}_i^{\infty}$$

e) $\lim_{n\to\infty} \|\mathscr{R}^n - \mathscr{R}^{\infty}\|_{\mathcal{L}(X)} = 0 \text{ and } \lim_{n\to\infty} \bar{\lambda}_i^n = \bar{\lambda}_i^{\infty}, \lim_{n\to\infty} \bar{\psi}_i^n = \bar{\psi}_i^{\infty} \text{ for } 1 \le i \le \ell \text{ (if } \bar{\lambda}_i^{\infty} \text{ seperated)}$

Stefan Volkwein

Numerical Example: $\lambda - \omega$ PDE System

•
$$\lambda - \omega$$
 PDE system: $s = u^2 + v^2$, $\lambda(s) = 1 - s$, $\omega(s) = -\beta s$
 $\begin{pmatrix} u_t \\ v_t \end{pmatrix} = \begin{pmatrix} \lambda(s) & -\omega(s) \\ \omega(s) & \lambda(s) \end{pmatrix} \begin{pmatrix} u \\ v \end{pmatrix} + \begin{pmatrix} \sigma \Delta u \\ \sigma \Delta v \end{pmatrix}$

Homogeneous Boundary Conditions:

$$u = v = 0$$
 or $\frac{\partial u}{\partial n} = \frac{\partial v}{\partial n} = 0$

• Initial conditions: $u_{\circ}(x_1, x_2) = x_2 - 0.5$, $v_{\circ}(x_1, x_2) = (x_1 - 0.5)/2$





u for β=3 and t=100



u for β=1 and t=100



< D > < P > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D > < D

Numerical Example: Decay of the POD Eigenvalues for the λ - ω Systems

- $\lambda \omega$ PDE system: $s = u^2 + v^2$, $\lambda(s) = 1 s$, $\omega(s) = -\beta s$ $\begin{pmatrix} u_t \\ v_t \end{pmatrix} = \begin{pmatrix} \lambda(s) & -\omega(s) \\ \omega(s) & \lambda(s) \end{pmatrix} \begin{pmatrix} u \\ v \end{pmatrix} + \begin{pmatrix} \sigma \Delta u \\ \sigma \Delta v \end{pmatrix}$
- Homogeneous Boundary Conditions:

$$u = v = 0$$
 or $\frac{\partial u}{\partial n} = \frac{\partial v}{\partial n} = 0$



Related Literature

- T. Antoulas: Approximation of Large-Scale Dynamical Systems, 2005
- P. Holmes, J.L. Lumley, G. Berkooz, C.W. Rowley: Turbulence, Coherent Structures, Dynamical Systems and Symmetry, 2012
- K. Karhunen: Zur Spektraltheorie stochastischer Prozesse, 1945
- S. Lall, J.E. Marsden, S. Glavaski: Empirical model reduction of controlled nonlinear systems, 1999
- M. Loève: Functions aléatoire de second ordre, 1945
- L. Sirovich: Turbulence and the dynamics of coherent structures, 1987
- C.W. Rowley: Model reduction for fluids, using balanced proper orthogonal decomposition, 2005

• ...

- M. Gubisch, S. V.: POD reduced-order modelling for PDE-constrained optimisation, 2013
- K. Kunisch, S. V.: Control of Burgers' equation by a reduced order approach using POD, 1999
- K. Kunisch, S. V.: Galerkin POD methods for a general equation in fluid dynamics, 2002
- S. V.: Optimal control of a phase-field model using the POD, 2001

Reduced-Order Modeling (ROM) Utilizing the POD Method

Topics:

- POD reduced-order modeling
- A-priori error analysis for POD
- Convergence and rate of convergence results
- Extensions

< 口 > < 同 > < 回 > < 回 > < 回 > <

Abstract Linear Evolution Problem

- Function spaces: H, V separable Hilbert spaces, $V \hookrightarrow H$ dense and compact
- Gelfand triple: $V \hookrightarrow H \equiv H' \hookrightarrow V'$
- Time-dependent bilinear form: $a(t; \cdot, \cdot) : V \times V \to \mathbb{R}$ satisfying

 $\begin{aligned} &|\boldsymbol{\alpha}(t;\boldsymbol{\varphi},\tilde{\boldsymbol{\varphi}})| \leq \gamma \|\boldsymbol{\varphi}\|_{V} \|\tilde{\boldsymbol{\varphi}}\|_{V} & \forall \boldsymbol{\varphi}, \tilde{\boldsymbol{\varphi}} \in V \text{ a.e. in } [t_{\circ}, t_{f}] \\ &\boldsymbol{\alpha}(t;\boldsymbol{\varphi},\boldsymbol{\varphi}) \geq \gamma_{1} \|\boldsymbol{\varphi}\|_{V}^{2} - \gamma_{2} \|\boldsymbol{\varphi}\|_{H}^{2} & \forall \boldsymbol{\varphi} \in V \text{ a.e. in } [t_{\circ}, t_{f}] \end{aligned}$

with time-independent constants γ , $\gamma_1 > 0$ and $\gamma_2 \ge 0$

- Solution Hilbert space: $W(t_{\circ}, t_{f}) = \{\varphi \in L^{2}(t_{\circ}, t_{f}; V) | \varphi_{t} \in L^{2}(t_{\circ}, t_{f}; V')\}$ $\Rightarrow W(t_{\circ}, t_{f}) \hookrightarrow C([t_{\circ}, t_{f}]; H), \text{ i.e., } y(t) \in H \text{ is meaningful for all } t \in [t_{\circ}, t_{f}]$
- Input/control space: $\mathcal{U} = L^2(t_\circ, t_f; U) \simeq \mathcal{U}'$ with $U = \mathbb{R}^{N_U}$, $U = L^2(\Omega)$ or $U = L^2(\Gamma)$
- Linear evolution problem: find $y \in W(t_{\circ}, t_{f})$ satisfying $y(t_{\circ}) = y_{\circ}$ in H and

 $\frac{\mathrm{d}}{\mathrm{d}t}\langle \mathbf{y}(t), \boldsymbol{\varphi} \rangle_{H} + \mathbf{a}(t; \mathbf{y}(t), \boldsymbol{\varphi}) = \langle (f + \mathscr{B}\mathbf{u})(t), \boldsymbol{\varphi} \rangle_{V', V} \quad \forall \boldsymbol{\varphi} \in V \text{ a.e. in } (t_{\circ}, t_{f}]$

for given $y_{\circ} \in H$, $f \in L^{2}(t_{\circ}, t_{f}; V')$ and bounded, linear $\mathscr{B} : \mathfrak{U} \to L^{2}(t_{\circ}, t_{f}; V')$

• Solvability: there is a unique solution $y \in W(t_{\circ}, t_{f})$ with

 $\|\mathbf{y}\|_{W(t_{\circ},t_{f})} \leq C(\|\mathbf{y}_{\circ}\|_{H} + \|f\|_{L^{2}(t_{\circ},t_{f};V')} + \|\mathbf{u}\|_{\mathcal{U}})$

with a constant C > 0 independent of y_{\circ} , f, and u

Affine Linear Representation of the Solution

• Linear evolution problem: find $y \in W(t_{\circ}, t_{f})$ satisfying $y(t_{\circ}) = y_{\circ}$ in H and

 $\frac{\mathrm{d}}{\mathrm{d}t}\langle y(t), \varphi \rangle_{H} + a(t; y(t), \varphi) = \langle (t + \mathscr{B}u)(t), \varphi \rangle_{V', V} \quad \forall \varphi \in V \text{ a.e. in } (t_\circ, t_f]$ (EVP)

for given $y_{\circ} \in H$, $f \in L^{2}(t_{\circ}, t_{f}; V')$ and bounded, linear $\mathscr{B} : \mathfrak{U} \to L^{2}(t_{\circ}, t_{f}; V')$

• Particular solution: $\hat{y} \in W(t_{\circ}, t_{f})$ solves $\hat{y}(t_{\circ}) = y_{\circ}$ in H and

$$\frac{\mathrm{d}}{\mathrm{d}t}\langle \hat{y}(t), \varphi \rangle_{H} + a(t; \hat{y}(t), \varphi) = \langle f(t), \varphi \rangle_{V', V} \quad \forall \varphi \in V \text{ a.e. in } (t_{\circ}, t_{f}]$$

- Control-to-state mapping: $\mathscr{S} : \mathcal{U} \to W(t_{\circ}, t_{f}), w = \mathscr{S}u$ solves $w(t_{\circ}) = 0$ in H and $\frac{\mathrm{d}}{\mathrm{d}t} \langle w(t), \varphi \rangle_{H} + a(t; w(t), \varphi) = \langle (\mathscr{B}u)(t), \varphi \rangle_{V', V} \quad \forall \varphi \in V \text{ a.e. in } (t_{\circ}, t_{f}]$
 - $\Rightarrow \mathscr{S}$ linear and bounded
- Affine linear representation of the solution to (EVP): $y = \hat{y} + \mathscr{S}u$
- Regularity: $y \in C([t_\circ, t_f]; V)$ if $a(t; \cdot, \cdot) = a(\cdot, \cdot), y_\circ \in V$ and $f, \mathscr{B}u \in L^2(t_\circ, t_f; H)$

Continuous Variant of POD for the Evolution Problem

- POD setting: X = H and X = V, $y^1 = \mathscr{S}u$ ($\mathscr{O} = 1$), $\mathcal{V} = \operatorname{span} \{y^1(t) | t \in [t_\circ, t_f]\}$, $d = \dim \mathcal{V}$
- Continuous variant of POD: for any $\ell \in \{1, \dots, d\}$ solve

$$\min \int_{t_o}^{t_f} \left\| y^1(t) - \sum_{i=1}^{\ell} \langle y^1(t), \psi_i \rangle_X \psi_i \right\|_X^2 \mathrm{d}t \quad \text{s.t.} \quad \{\psi_i\}_{i=1}^{\ell} \subset X, \ \langle \psi_i, \psi_j \rangle_X = \delta_{ij}, \ 1 \le i, j \le \ell \quad (\mathbf{P}_{\infty}^{\ell})$$

- Integral operator: $\mathscr{R}: X \to X$ with $\mathscr{R}\psi = \int_{t_0}^{t_f} \langle \psi, y^1(t) \rangle_X y^1(t) dt$
- POD basis of rank ℓ : $\{\psi_i\}_{i=1}^{\ell} \subset X, V^{\ell} = \operatorname{span} \{\psi_1, \dots, \psi_{\ell}\}$

$$\|y^{1} - \mathscr{P}^{\ell}y^{1}\|_{L^{2}(t_{o}, t_{f}; X)}^{2} = \int_{t_{o}}^{t_{f}} \|y^{1}(t) - \sum_{i=1}^{\ell} \langle y^{1}(t), \psi_{i} \rangle_{X} \psi_{i}\|_{X}^{2} dt = \sum_{i=\ell+1}^{d} \lambda_{i}$$

with
$$\mathscr{P}^{\ell}\psi = \sum_{i=1}^{\ell} \langle \psi, \psi_i \rangle_X \psi_i$$
 for $\psi \in X$

- **Reduced-order model**: use V^{ℓ} as the solution and test space instead of V \Rightarrow low-dimensional model since $\ell \ll \dim V = \infty$ (in practise: $\ell \ll \dim V^{\mathcal{N}} = \mathcal{N}$)
- **Regularity**: if $(\mathscr{S}u)(t) \in V$ a.e. in $[t_{\circ}, t_{f}]$, then $\{\psi_{i}\}_{i=1}^{\ell} \subset V$ holds even for X = H

• Linear evolution problem: find $y \in W(t_{\circ}, t_{f})$ satisfying $y(t_{\circ}) = y_{\circ}$ in H and

 $\frac{\mathrm{d}}{\mathrm{d}t}\langle \mathsf{y}(t), \varphi \rangle_H + \mathsf{a}(t; \mathsf{y}(t), \varphi) = \langle (f + \mathscr{B}\mathsf{u})(t), \varphi \rangle_{V', V} \quad \forall \varphi \in V \text{ a.e. in } (t_\circ, t_f]$

• Particular solution: $\hat{y} \in W(t_{\circ}, t_{f})$ solves $\hat{y}(t_{\circ}) = y_{\circ}$ in H and

$$\frac{\mathrm{d}}{\mathrm{d}t} \langle \hat{y}(t), \varphi \rangle_H + a(t; \hat{y}(t), \varphi) = \langle f(t), \varphi \rangle_{V', V} \quad \forall \varphi \in V \text{ a.e. in } (t_\circ, t_f]$$

• POD control-to-state mapping: $\mathscr{S}^{\ell}: \mathcal{U} \to W(t_{\circ}, t_{f}), w^{\ell} = \mathscr{S}^{\ell} u$ solves $w^{\ell}(t_{\circ}) = 0$ in H and

$$\frac{\mathrm{d}}{\mathrm{d}t}\langle \mathsf{w}^\ell(t), \psi \rangle_H + a(t; \mathsf{w}^\ell(t), \psi) = \langle (\mathscr{B}u)(t), \psi \rangle_{V', V} \quad \forall \psi \in V^\ell \text{ a.e. in } (t_\circ, t_f)$$

 $\Rightarrow \mathscr{S}^\ell$ linear and bounded

• POD solution form: $y^{\ell} = \hat{y} + \mathscr{S}^{\ell} u$

 $\Rightarrow y^{\ell}(0) = y_{\circ}$ in *H*, i.e., no POD error in the initial condition

• POD a-priori error: convergence result for $||y - y^{\ell}||$ and $||\mathscr{S} - \mathscr{S}^{\ell}||_{\mathcal{L}(X)}$?

POD A-Priori Estimation

• POD setting:
$$X = V, y^1 = \mathscr{P}u, V^\ell = \operatorname{span} \{\psi_1, \dots, \psi_\ell\}, \mathscr{P}^\ell \psi = \sum_{i=1}^\ell \langle \psi, \psi_i \rangle_V \psi_i$$

$$\left\|\mathscr{S}\mathbf{u}-\mathscr{P}^{\ell}(\mathscr{S}\mathbf{u})\right\|_{L^{2}(t_{o},t_{f};V)}^{2}=\int_{t_{o}}^{t_{f}}\left\|Y^{1}(t)-\sum_{i=1}^{\ell}\langle Y^{1}(t),\psi_{i}\rangle_{V}\psi_{i}\right\|_{V}^{2}\mathrm{d}t=\sum_{i=>\ell}\lambda_{i}$$

Decomposition:

$$y^{\ell}(t) - y(t) = \hat{y}(t) + (\mathscr{S}^{\ell} U)(t) - \hat{y}(t) - (\mathscr{S} U)(t)$$

= $\underbrace{(\mathscr{S}^{\ell} U)(t) - \mathscr{P}^{\ell}((\mathscr{S} U)(t))}_{=:\vartheta^{\ell}(t) \in V^{\ell}} + \underbrace{\mathscr{P}^{\ell}((\mathscr{S} U)(t)) - (\mathscr{S} U)(t)}_{=:\rho^{\ell}(t) \in (V^{\ell})^{\perp}} = \vartheta^{\ell}(t) + \rho^{\ell}(t)$

• Estimate for ρ^{ℓ} : $\int_{t_{o}}^{t_{f}} \|\rho^{\ell}(t)\|_{V}^{2} dt = \int_{t_{o}}^{t_{f}} \|\mathscr{P}^{\ell}((\mathscr{S}u)(t)) - (\mathscr{S}u)(t)\|_{V}^{2} dt = \sum_{i>\ell} \lambda_{i}$

• Estimate for ϑ^{ℓ} : use the evolution equation

 $\frac{\mathrm{d}}{\mathrm{d}t} \langle \vartheta^{\ell}(t), \psi \rangle_{H} + a(t; \vartheta^{\ell}(t)(t), \psi) = \langle (\mathscr{S}u)_{t}(t) - \mathscr{P}^{\ell}((\mathscr{S}u)_{t}(t)), \psi \rangle_{V', V} \; \forall \psi \in V^{\ell} \text{ a.e. in } (t_{\circ}, t_{f}]$ and choose $\psi = \vartheta^{\ell}(t) \in V^{\ell}$

POD A-Priori Error for Abstract Linear Evolution Problems

Theorem (Kunisch/V.'01, Hinze/V.'08, Tröltzsch/V.'09, Gubisch/V.'13)

$$\begin{aligned} X &= V, \, \mathcal{V} = \text{span} \left\{ y^{k}(t) \mid t \in [t_{\circ}, t_{f}], \, 1 \leq k \leq \wp \right\} \\ \text{a) Snapshot } y^{1} &= \mathscr{S}u, \, y = \hat{y} + \mathscr{S}u, \, y^{\ell} = \hat{y} + \mathscr{S}^{\ell}u: \\ & \|y - y^{\ell}\|_{W(t_{\circ}, t_{f})}^{2} \leq \sum_{i > \ell} \lambda_{i} + C_{1} \|(\mathscr{S}u)_{t} - \mathscr{P}^{\ell}(\mathscr{S}u)_{t}\|_{L^{2}(t_{\circ}, t_{f}; V')}^{2} \\ \text{b) Snapshots } y^{1} &= \mathscr{S}u \text{ and } y^{2} = (\mathscr{S}u)_{t} \in L^{2}(t_{\circ}, t_{f}; V): \\ & \|y - y^{\ell}\|_{W(t_{\circ}, t_{f})}^{2} \leq C_{2} \sum_{i \geq \nu} \lambda_{i} \end{aligned}$$

c) If $\mathscr{S}u \in H^{1}(t_{\circ}, t_{f}; V)$ for all $\tilde{u} \in \mathfrak{U}$, then $\lim_{\ell \to \infty} \|\mathscr{S} - \mathscr{S}^{\ell}\|_{\mathcal{L}(\mathfrak{U}, V)} = 0$ In particular, $\lim_{\ell \to \infty} \|y(\tilde{u}) - y^{\ell}(\tilde{u})\|_{W(t_{\circ}, t_{f})} = 0$ for any $\tilde{u} \in \mathfrak{U}$

• FE approximation quality: $\|\varphi - \mathscr{P}^h \varphi\|_H + h \|\varphi - \mathscr{P}^h \varphi\|_V = \mathscr{O}(h^2)$ for all $\varphi \in Z \subset V$

• POD approximation quality:
$$\|\varphi - \mathscr{P}^{\ell}\varphi\|_{L^{2}(t_{o},t_{f};V)}^{2} = \mathscr{O}\left(\sum_{i=\ell+1}^{d} \lambda_{i}\right)$$
 for all $\varphi \in \mathcal{V} \subset V$

• Extension for the case X = H (Singler'13)

Stefan Volkwein

Numerical Example for the Modified POD Galerkin Scheme

- Problem: linear heat equation on $(t_{\circ}, t_{f}) = (0,3)$ and $\Omega = (0,2)$
- Discretization: piecewise linear FE and Crank-Nicolson with a total error of 10⁻⁵
- Continuous and discontinuous initial condition: $y_{\circ}(x) = \sin(\pi x/2)$ without/with noise



- Fully discretized problems: temporal error, asymptotic analysis, case X = H
- A-priori error analysis for nonlinear systems: e.g., Navier-Stokes and battery models
- A-priori error analysis with respect to the "truth" approximation
- Optimal snapshot locations: goal-oriented choice of snapshots
- Efficient POD-Galerkin for nonlinear problems: POD-(D)EIM
- Parameterized PDEs: POD-Greedy algorithm
- POD and Balancing: utilize observability (i.e., dual) information

• ...

- Bui-Thanh, Chapelle, Chaturantabut, Hinze, Iliescu, Kemper, Navon, Petzold, Pinnau, Sachs, Rowley, Schneider, Schu, Singler, Sorensen, Willcox, Yvon, ...
- M. Gubisch and S. Volkwein: POD reduced-order modelling for PDE-constrained optimisation, 2013
- M. Hinze, S. V.: POD surrogate models for nonlinear dynamical systems: error estimates and suboptimal control, 2006
- M. Hinze, S. V.: Error estimates for abstract linear-quadratic optimal control problems using POD, 2008
- K. Kunisch, S. V.: Galerkin POD methods for parabolic problems, 2001
- K. Kunisch, S. V.: Optimal snapshot location for computing POD basis functions, 2010
- O. Lass, S.V.: Adaptive POD basis computation for parametrized nonlinear systems using optimal snapshot location, 2012
- E.W. Sachs and S. Volkwein: POD-Galerkin Approximations in PDE-Constrained Optimization, 2010